



AC/DC adapter

Model: **AK-ND-59**



LENOVO POWER USB
20.0 V / 2.00 A / 40 W



| | |
|--------------------------|---------------------|
| Product code | AK-ND-59 |
| Product type | AC/DC adapter |
| Compatible with | Lenovo |
| Series | Dedicated |
| Supply voltage | 100-250 V |
| Power consumption | < 1.5 A |
| Efficiency | > 80 % |
| Output voltage | 20 V |
| Output amperage | 2.0 A |
| Outlet cord length | 1.2 m |
| Output connector | Lenovo Power USB |
| Maximum power | 40 W |
| Power inlet | CEE 7/16 (Europlug) |
| Mechanical switch | None |
| Ground wire | Yes |
| Soft start | Yes |
| OVP | Yes |
| OCP | Yes |
| OPP | Yes |
| OTP | Yes |
| SCP | Yes |
| Ferrite filter | Yes |
| USB connector | None |
| Power cable included | No |
| Material | ABS |
| Product color | Black |
| Display | None |
| MTBF | 100000 h |
| Temperature | 5 - 50 °C |
| Package | EcoBox |
| Product size (L x W x H) | 99 x 60 x 30 mm |
| Package size (L x W x H) | 190 x 92 x 38 mm |
| Net weight | 183 g |
| Gross weight | 232 g |
| CE compatibility | Yes |
| FCC compatibility | Yes |
| RoHS compatibility | Yes |
| REACH compatibility | Yes |
| EAN code | 5901720134462 |
| Warranty | 24 months |



Description

Akyga® AK-ND-59 is a **Lenovo®'s notebooks dedicated power supply** for devices powered with **20V/2.0A, 40W** power and **Power USB** plug.

The cord is equipped with a ferrite core that prevents and protects devices from mode current and high frequency noise. A set of protectors (OVP, OTP, OPP, SCP and OCP) guarantees 100% secure, stable work both powered device and the power supply. Additional safety for the equipment is provided by the soft start technology, which neutralizes the shock of the first stroke of current during the device startup.

All Akyga power supplies are provided in an environmentally friendly EcoBox.

A power supply dedicated to Lenovo / IBM laptops.

We encourage you to use our [notebook power adapter search engine](#).